# RPi Node-Red: Neopixel LED Ring

# Goal:

Use string injection nodes and a specific LED ring node to control a LED ring

### What You Will Learn:

Basic Node-Red Programming

#### What You Need to Know:

• <u>RPi Node-Red: LED Tutorial</u>

# **Parts List:**



12 pixel LED ring



3x male to female jumper wires

## **Getting Started:**

#### Setting up the Hardware

×



Use jumper cables to attach the LED ring as in the image. Attach the red wire to +5v, the black to ground, and the white data line to GPIO pin 18.

#### Setting up Node-Red

Start Node-Red and navigate to <u>127.0.0.1:1880</u> using the web browser.

Drag in the 'rpi neopixels' node; and double click on it to start editing its properties.

■< Bode-RED						Deploy -		
Q filter nodes	ow 1	Edit rpi-neopixe	ls node		info	debug		
Q watch		Delete	Delete Cancel Done			✓ Information		
feedparse o		✓ node propert	✓ node properties			"b97a5b05.a72748"		
						rpi-neopixels		
		O LEDs	12 in the string			show more 👻		
<ul> <li>Raspberry Pi</li> </ul>		🕫 Mode	Bar - Number of pixels	•	✓ Node Help			
rpi gpio		E Declarated			Raspberry Pi n	ode to drive a string of		
rpi gpio		Background	HIML colour name or rrr,ggg,b		Defaults to a ba	ar chart style mode using		
rpi mouse		Foreground	HTML colour name or rrr,ggg,b	bb	configured fore	ground and background		
mi keyboard		O Wipe time	40 mS Pixel order	RGB 🔻	pixel) type gau	aiso display a needle (single ge.		
		O Brightness	15 (0-100)		It can accept a	number in msg.payload		
takephoto					that can be either the humber of pixels, or a percentage of the total length. If you want to change the foregound colour,			
edborg			Apply gamma correction					
Trpi neopixels		Name	My LED ring		you can send a	CSV of html colour,length.		
Sense HAT	neopixels	s s		colour name. Here is a list of html colour				
Sense TAT 9					names.			
Sense HAT					You can also se	elect shift modes where a		
👹 rpi srf					Hold down	t when you click on		
v network					a node	to also select all of its		
					connected nodes			
ping v (		> node setting	5					
* *								

Set the **LEDs** field to the number of LED on the ring: 12. Set the **Mode** to 'bar – Number of pixels'. The other fields are all optional, but it might be nice to lower the **Brightness**, here I lowered it to 15 to lower eye damage. The LED ring can be painfully bright if you are indoors.

🛞 🌐 🛅 📰 🔅 🔇 🗾 Node-RED console	💽 Node-RED - Chromium 🗾 [pi@raspber	rypi: ~]	V2 🖇 🛜	7 % 01:48						
Node-RED - Chromium										
Node-RED ×				٢						
← → C ③ 127.0.0.1:1880/#flow/444e14ce.77050c		☆ 🔟 😳 🗄								
T <sup>3</sup> Alliance 🖉 Node-RED										
RED			_	🖥 Deploy 🔹 📃						
Q filter nodes Flow 1	Edit inject node		info	debug						
✓ input	Delete	Cancel Done	<ul> <li>Information</li> </ul>	Î						
	✓ node properties		Node "d3a	a4b0b5.2b65f"						
			Name Send	'Blue' Command						
catch p	■ Payload 🚽 az Blue		Type inject	t						
status Send 'Blue' Command U				show more 💌						
	🖻 Торіс		Vode Help							
	Inject once after 1 se	conds, then	Injects a message in	to a flow either manually						
) mqtt	C Papagt interval	-	or at regular intervals	s. The message payload						
http -	Thereat		JavaScript objects or	r the current time.						
websocket	every 1 🗘 seconds	•	~ Outputs							
ten b	Namo Sand 'Blue' Command		payload	various						
	Send Dide Command		The configured pa	yload of the message.						
li dp gbu	Note: "interval between times" and "at a specific time" will use cron.			string 👻						
😳 Watson IoT	"interval" should be less than 596 hours. See info hox for details									
Serial D										
v output > node settings										

Next we drag in the 'injection' node, the LED ring node reads strings of text-based commands, and turns them into output on the ring.

We configure our injector like this; setting up **Payload** to be a string, and contents to be 'Blue'. Set the checkbox for **Inject once after** and set the timer to 1 seconds. **Repeat** can be set to 'none'.



Connect the two nodes up like this, check your wiring from the start of the tutorial; and then you're ready to hit **Deploy**. If everything is setup correctly the LED ring should display blue within a few seconds.

The command 'Purple' sets the **background** color to purple on the LED ring.

When the LED ring is initialized all the LEDs are changed to the background color, this can also be set in the node preferences as one of the fields we ignored earlier.

If you read the 'Node Help' page for the LED ring node you can see further commands.

For example if we change the payload in the injection node to '5,Red' and Deploy then the first 5 LED will be turned Red; the rest of the LED will remain at the **background** color we can set in the properties field.

🛞 🍈 🔁 🗾 🗰 🔇 🗾 Node-RED console	Node-RED - Chrom [[pi] [pi] pi@raspberrypi: ~	V2 🖇 🛜 📣 🛛 7 % 02:07 🔺									
Node-RED - Chromium _ @ ×											
Node-RED ×		٨									
← → C ③ 127.0.0.1:1880/#flow/444e14ce.77050c	☆ 🕅 🤨 🗄										
🏌 T <sup>3</sup> Alliance 🚾 Node-RED											
Node-RED											
Q filter nodes Flow 1	Edit inject node	info debug									
~ input	Delete Cancel Done	specific payload value. The default payload									
⇒ inject	✓ node properties										
i catch	Sequence Payload $\rightarrow a_z$ 5,Red	The node also supports injecting strings, numbers, booleans, JavaScript objects, or									
status	S Topic	By default, the node is triggered manually by									
link	Inject once after 1 seconds then	clicking on its button within the editor. It can									
) mqtt	inject once after I seconds, then	according to a schedule.									
http	C Repeat none v	It can also be configured to inject once each									
websocket	Name Send '5,Red Command	The maximum Interval that can be specified									
tcp o	Note: "interval between times" and "at a specific time" will use cron.										
de de	"interval" should be less than 596 hours. See info box for details.	you should consider using a scheduler node									
🔅 Watson IoT 🖸		2 ×									
N serial		Switch flow tabs with $ctrl-\hat{1}j$ and $ctrl-\hat{1}k$									
~ output	CULTUR										
A V											

Another possible command is a range of pixels, for example the command '3,7,Red' will set pixels 3-7 Red.

The Color names the LED ring will accept can be found here on Wikipedia : <a href="https://en.wikipedia.org/wiki/Web\_colors">https://en.wikipedia.org/wiki/Web\_colors</a>

#### CONTINUING

the next step is to connect this knowledge with other tutorials, see other tutorials to maybe connect the LED ring to a physical button, or use it in concert with other outputs like speakers.

More advanced logic can be used to turn the LED ring into a clock, or dial.

• Node-Red Led tutorial